











Thank you for your purchase of Premio OSS424-D5 Storage Server System!

1. Check the Content of the box. Please confirm that your package contains the following:


#	Description	Image / Description	Qty
1	OSS424-D5 Enclosure		1
2	Motherboard	Tyan S7100GM2NR	1
3	CPU and memory	Intel Skylake and DDR4	Opt.
4	IO Cards		Opt.
5	Heatsink		2
6	2x 2.5" Drive Bay		Opt.
7	8x 2.5" Drive Bay		Opt.
8	Slide Rail Kit + Screws		1 set
9	Power Cable*		2
10	Serial Cable*		1

* Inside the accessories box. Box may consist of screw sets for rail kit or drives. If any items are missing, please contact your reseller or sales rep.


2. Get Familiar with the Unit.

OSS424-D5 is a storage server supporting dual Intel processor and front tray-less 24x 3.5" HDDs, optional rear 2x or 8x 2.5" drive bays powered by Tyan S7100GM2NR motherboard.

Front view of the unit




Rear view of the unit




3. Remove the Top Covers of the unit as follows:

First, remove the middle cover:




Proceed to remove the motherboard cover:




4. Inspect the Inside of the unit.

Internal components comprise of a Tyan motherboard, an expander board, optional rear 2x and 8x 2.5" bays, 3x internal 120mm fan modules (electronically attached to the motherboard).



To install OS disk(s), a space for 2 OS disks is available on the left inner wall of the chassis.



Installation and service of this product should be conducted by a trained personnel to avoid bodily injury from electric shock or heavy object




Observe ESD (Electrostatic Discharge) practices during integration to avoid possible damage to the board and / or other components

5. Install Motherboard Components (CPU, heatsink, memory) using the guidelines below. For further details, refer to the motherboard TPS.

- Support Intel Xeon Skylake Processor Family
- 2x LGA3647 Sockets
- Max up to 205W TDP
- Intel C621 PCH Chipset


- 6+6 DDR4 RDIMM/LRDIMM 2666
- Up to 384GB RDIMM / 768GB LRDIMM / 1536GB RDIMM 3DS
- 6 Channels per CPU, 1.2V
- Populate from A0 → F0

- PCIe1, PCE3 (Gen3x16), PCIe2 (Gen3x8) f/ CPU0
- PCIe5, PCE7 (Gen3x16), PCIe4, PCIe6 (Gen3x8) f/ CPU1



6. Remove the Inner Rail from the slide rail.


- 1-2 Pull the inner rails out. Pull the blue release tab when it hits a stop.
- 3-4 Keep extending inner rail and pull the white detach tab when it hits the second stop




- 5-6 Unretract the mid rail by pulling the latch on the mid rail

7. Install Inner Rails to the enclosure.

Yellow circle is for standoff pins




8. Install the Outer Rails to the Rack as follows:




Red rectangles are locations for slide rail position (front and rear posts)

Place square nut at yellow circles for enclosure screws (front only)


- 1-2 Snap the rear part of slide rail to rear posts
- 3-4 Snap the front part of slide rail to front posts



To remove slide rails, use the latches to undo the assembly as follows:



9. Install the Unit to the Rack as follows:




For a complete instruction on how to install unit to the rack, please follow the Slide Rail Installation Guide.




At least two people are recommended for mounting process.

10. Install 3.5" Drives to the enclosure as illustrated:



To remove the disk, open the drive bay cover, pull the handle out so that drive slightly slides out, and pull out the drive with hand.

11. Install 2.5" Drives to the enclosure as illustrated:



12. Plug in the Power Cords to the AC receptacles on the back of the unit.



13. Press the Power Button on the front of the unit and for the system to boot up.



14. Access the Serial Console (when necessary) by

connecting a serial audio cable to the console port at the back of the unit. See picture for detail. Use a terminal console with baud set 38400, 8, N, 1, N. Type “help -a” for a list of commands.

